



Features:

- TVI/AHD/CVI signal to CVBS/VGA/HDMI up to 1080p
- HDMI output format: 720P@50/60Hz, 1080P@50/60Hz
- HDMI input can compatible several format of DVI : 800X600、1024X768,1280X1024、1360X768, 1680X1050、1920X1080@50_60Hz ect .
- Default signal output of the converter is HDMI/VGA ,it can be switched to VGA/BNC by pushing button .
- Video input system: NTSC / PAL (Automatic detection and adaptive)
- VGA and BNC signal can be connected to the converter at the same time ,the output signal can be switched by switch .
- Compatible with HDCP, HDMI1.4
- Provides HD analog signal TVI/CVI/AHD input interface
- Provides HD digital signal HDMI(720P@60Hz/1080p@60hz) output interface .
- Provides power adapter 5-12V DC interface
- Support AHD/CVI/TVI signal 500m
- Support HDMI1.4 version and compatible below
- Support video output smoothly , without signal loss , screen polarized and screen shaking
- CE, FCC, RoHS certificate

Switch Instruction:

- 1>When button 2 is HDMI output, function of button 1 is to switch output resolution between 720p and 1080p

2>When button 2 is VGA output , function of button 1 is to switch output resolution with between 600p and 1080p .

3> When button 2 is CVBS output , function of button 1 is to switch PAL /NTSC video source